

Aluminum electrolytic capacitors

Axial-lead capacitors

Series/Type: B43698

Date: December 2010

© EPCOS AG 2010. Reproduction, publication and dissemination of this publication, enclosures hereto and the information contained therein without EPCOS' prior express consent is prohibited.



Axial-lead capacitors

High performance - 105 °C

B43698

Applications

■ Electronic ballasts

Features

- Extremely long useful life
- Very high ripple current capability
- Very high voltage capability 550 V DC/85 °C/5000 h 500 V DC/105 °C/10000 h
- Outstanding performance



- Charge/discharge-proof, polar
- Aluminum case with insulating sleeve
- Negative pole connected to case
- Axial leads, welded to ensure perfect electrical contact

Taping and packing

- Bulk
- Pallet package
- Capacitors with $d \times I \le 16 \times 30$ mm are also available taped on reel.









Specifications and characteristics in brief

Rated voltage V _R	450 V DC					
Surge voltage V _S	550 V DC at 105 °C					
Rated capacitance C _R	6.8 33 μF					
Capacitance tolerance	-10/+30% ≙ Q					
Leakage current I _{leak}	/C _P	V _P \0.7				
(5 min, 20 °C)	$I_{leak} \le 0.3 \mu\text{A} \cdot \left(\frac{C_R}{\mu\text{F}}\right)$	· ·	l μA			
Self-inductance ESL ¹⁾	Diameter d (mm)	12	13.3	14	16	18
	Length I (mm)	Approx.	ESL (nH)			
	30	21	_	24	29	34
	39	23	28	_	33	38
Useful life		Requirer	nents:			
105 °C; V _R ; I _{AC,R}	> 15000 h	Δ C/C	≤ ±30% (of initial va	alue	
105 °C; 500 V DC; I _{AC,R}	> 10000 h	ESR	≤ 3 times	initial spe	ecified limi	it
90 °C; V _R ; I _{AC,R}	> 50000 h	I _{leak}	≤ initial s	pecified li	mit	
85 °C; 500 V DC; I _{AC,R}	> 50000 h					
40 °C; V _R ; 2.1 ⋅ I _{AC.R}	> 500000 h					
40 °C; 500 V DC;						
2.2 · I _{AC,R}	> 250000 h					
Voltage endurance test		Post test	requirem	ents:		
105 °C; V _R	7500 h	ΔC/C	≤ ±10% (of initial va	alue	
		ESR	≤ 1.3 tim	es initial s	pecified li	mit
		I _{leak}	≤ initial s	pecified li	mit .	
Vibration resistance test	To IEC 60068-2-6, tes					
	Frequency range 10 l	Hz 55 H	lz, displac	ement am	plitude 0.7	75 mm,
	acceleration max. 10	g, duratio	$n 3 \times 2 h$.			
	Capacitor mounted by its wire leads at a distance of (6 \pm 1) mm from			ım from		
	the case and addition	ally clamp	ed by the	case.		
IEC climatic category	To IEC 60068-1:					
	40/105/56 (-40 °C/+105 °C/56 days damp heat test)					
Detail specification	Similar to CECC 30301-801					
Sectional specification	IEC 60384-4					

¹⁾ If optimum circuit design is used, the values are lower by 30%.






High performance - 105 °C

Axial-lead capacitors

Dimensional drawing



Dimensions, weights and packing units

d×I	$d_{max} \times I_{max}$	Wire w	Approx. weight	Packing uni	ts (pcs.)	
mm	mm	mm	g	Bulk	Pallet	Reel
12×30	12.5 × 30.5	0.8	5.1	600	288	450
12×39	12.5×40	0.8	6.5	500	288	_
13.3×39	14.0×40	0.8	8.0	400	200	_
14×30	14.5×30.5	0.8	6.8	400	200	350
16×30	16.5×30.5	0.8	8.9	350	180	250
16×39	16.5×40	0.8	11.7	300	180	_
18×30	18.5×30.5	1.0	11.1	300	160	_
18×39	18.5×40	1.0	14.7	250	160	_







Case dimensions and ordering codes

V_R	C _R	Case	Ordering code	Ordering code	Ordering code
	100 Hz	dimensions	Bulk	Pallet package	Reel
	20 °C	d×I			
V DC	μF	mm			
450	6.8	12 × 30	B43698A5685Q000	B43698A5685Q007	B43698A5685Q009
	10	12 × 39	B43698B5106Q000	B43698B5106Q007	
	10 ∇	14 × 30	B43698A5106Q000	B43698A5106Q007	B43698A5106Q009
	15	13.3×39	B43698B5156Q000	B43698B5156Q007	
	15 ∇	16 × 30	B43698A5156Q000	B43698A5156Q007	B43698A5156Q009
	22	16 × 39	B43698A5226Q000	B43698A5226Q007	
	22 ∇	18 × 30	B43698B5226Q000	B43698B5226Q007	
	33	18 × 39	B43698A5336Q000	B43698A5336Q007	

[∇] Variant with different case dimensions

Technical data

$\overline{C_{R}}$	ESR _{typ}	ESR _{max}	ESR _{max}	ESR _{max}	Z _{max}	I _{AC,max}	I _{AC,max}	I _{AC,R}
100 Hz	100 Hz	100 Hz	100 Hz	10 kHz	100 kHz	10 kHz	10 kHz	10 kHz
20 °C	20 °C	20 °C	−25 °C	20 °C	20 °C	60 °C	85 °C	105 °C
μF	Ω	Ω	Ω	Ω	Ω	Α	Α	Α
$V_{R} = 450 \text{ V}$	/ DC							
6.8	7.2	12.0	180	5.5	5.4	1.26	1.03	0.54
10	4.9	8.1	120	3.8	3.7	1.74	1.42	0.75
10 ∇	4.9	8.1	120	3.8	3.7	1.65	1.34	0.71
15	3.2	5.4	80	2.5	2.4	2.24	1.82	0.96
15 ∇	3.2	5.4	80	2.5	2.4	2.13	1.74	0.92
22	2.2	3.7	50	1.7	1.6	2.94	2.40	1.26
22 ∇	2.2	3.7	50	1.7	1.6	2.68	2.19	1.15
33	1.5	2.5	40	1.2	1.1	3.73	3.04	1.60

[∇] Variant with different case dimensions






High performance - 105 °C


Useful life

depending on ambient temperature T_A under ripple current operating conditions at $V_R^{1)}$ $V_B = 450 \ V$



Useful life

depending on ambient temperature T_A under ripple current operating conditions at $V_{op}^{1)}$ $V_{op} = 500 \text{ V}$




¹⁾ Refer to chapter "General technical information, 5.3 Calculation of useful life" for an explanation on how to interpret the useful life graphs.








Frequency factor of permissible ripple current I_{AC} versus frequency f




Frequency characteristics of ESR

Typical behavior




Equivalent series resistance ESR versus frequency f

Typical behavior for 22 µF/450 V



Impedance Z versus frequency f

Typical behavior for 22 µF/450 V







High performance - 105 °C

Cautions and warnings

Personal safety

The electrolytes used by EPCOS have not only been optimized with a view to the intended application, but also with regard to health and environmental compatibility. They do not contain any solvents that are detrimental to health, e.g. dimethyl formamide (DMF) or dimethyl acetamide (DMAC).

Furthermore, part of the high-voltage electrolytes used by EPCOS are self-extinguishing. They contain flame-retarding substances which will quickly extinguish any flame that may have been ignited.

As far as possible, EPCOS does not use any dangerous chemicals or compounds to produce operating electrolytes. However, in exceptional cases, such materials must be used in order to achieve specific physical and electrical properties because no safe substitute materials are currently known. However, the amount of dangerous materials used in our products has been limited to an absolute minimum. Nevertheless, the following rules should be observed when handling aluminum electrolytic capacitors:

- Any escaping electrolyte should not come into contact with eyes or skin.
- If electrolyte does come into contact with the skin, wash the affected parts immediately with running water. If the eyes are affected, rinse them for 10 minutes with plenty of water. If symptoms persist, seek medical treatment.
- Avoid breathing in electrolyte vapor or mists. Workplaces and other affected areas should be well ventilated. Clothing that has been contaminated by electrolyte must be changed and rinsed in water.







Product safety

The table below summarizes the safety instructions that must be observed without fail. A detailed description can be found in the relevant sections of chapter "General technical information".

Polarity Make sure that polar capacitors are connected with the right polarity. Make sure that polar capacitors are connected with the right polarity. Polarity Make sure that polar capacitors are connected with the right polarity. Basic construction of aluminum electrolytic capacitors: Reverse voltage Voltages polarity classes should be prevented by connecting a diode. Upper category temperature. Do not exceed the upper category temperature. Make periodic inspections of the capacitors. Before the inspection, make sure that the power supply is turned off and carefully discharge the electricity of the capacitors. Do not apply any mechanical stress to the capacitor terminals. Mounting position of screw-terminal capacitors Mounting of single-ended capacitors might be damaged if excessive force is applied to the lead wires. Avoid any compressive, tensile or flexural stress. Do not move the capacitor after soldering to PC board. Do not pick up the PC board by the soldered capacitors. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. The following maximum tightening torques must 11.3	Topic	Safety information	Reference
Polarity Make sure that polar capacitors are connected with the right polarity. Make sure that polar capacitors are connected with the right polarity. Polarity Make sure that polar capacitors are connected with the right polarity. Polarity Make sure that polar capacitors are connected aluminum electrolytic capacitors. Reverse voltage Voltages polarity classes should be prevented by connecting a diode. Upper category temperature. Do not exceed the upper category temperature. Maintenance Make periodic inspections of the capacitors. Before the inspection, make sure that the power supply is turned off and carefully discharge the electricity of the capacitors. Do not apply any mechanical stress to the capacitor terminals. Mounting position of screw-terminals (safety vent) upside down. The internal structure of single-ended capacitors might be damaged if excessive force is applied to the lead wires. Avoid any compressive, tensile or flexural stress. Do not move the capacitor after soldering to PC board. Do not pick up the PC board by the soldered capacitors bonot move the capacitor after soldering to PC board. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of the following maximum tightening torques must not be exceeded when connecting screw terminals: M5: 2 Nm M6: 2.5 Nm Soldering Do not exceed the specified time or temperature 11.5	Торіс	Salety information	
Polarity Make sure that polar capacitors are connected with the right polarity. Make sure that polar capacitors are connected with the right polarity. Peverse voltage Voltages polarity classes should be prevented by connecting a diode. Upper category temperature Do not exceed the upper category temperature. Make periodic inspections of the capacitors. Before the inspection, make sure that the power supply is turned off and carefully discharge the electricity of the capacitors. Do not apply any mechanical stress to the capacitor terminals. Mounting position of screw-terminal capacitors Mounting of single-ended capacitors Mounting of single-ended capacitors The internal structure of single-ended capacitors with screw terminals for the lead wires. Avoid any compressive, tensile or flexural stress. Do not move the capacitor after soldering to PC board. Do not pick up the PC board by the soldered capacitors. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals: M5: 2 Nm M6: 2.5 Nm Mointing or temperature 11.1.1 "Basic construction of aluminum electrolytic capacitors" 7.2 "Maximum permissible operating temperature" 10 "Maintenance" 11.1. "Mounting positions of capacitors with screw terminals on single-ended capacitors with screw terminals and positions of respective of the soldered capacitors on the PC board with a hole space different to the lead space specified. Robustness of terminals: M5: 2 Nm M6: 2.5 Nm Do not exceed the specified time or temperature 11.5			
with the right polarity. With the reverse voltage. With the reverse voltage. Waximum permissible operature. Waximum permissible operature. Waximum permissible operature. Waximum permissible operature. Waximum pertissite. Watimum pertissite. Waximum pertissite. Waximum pertissite. Waxi	Dolority	Make ourse that polar conscitors are connected	
Reverse voltage Voltages polarity classes should be prevented by connecting a diode. Upper category temperature Do not exceed the upper category temperature. Maintenance Make periodic inspections of the capacitors. Before the inspection, make sure that the power supply is turned off and carefully discharge the electricity of the capacitors. Do not apply any mechanical stress to the capacitor terminals. Mounting position of screw-terminal capacitors Mounting of single-ended capacitors The internal structure of single-ended capacitors might be damaged if excessive force is applied to the lead wires. Avoid any compressive, tensile or flexural stress. Do not move the capacitor on the PC board with a hole space different to the lead space specified. The following maximum tightening torques must not be exceeded when connecting screw terminals: M5: 2 Nm M6: 2.5 Nm Soldering Do not exceed the upper category temperature 3.1.6 "Reverse voltage" 7.2 "Maximum permissible operating ** "Maintenance" "Maintenance" "Maintenance" "Maintenance" "Maintenance" "Mounting positions of capacitors with screw terminals "Mounting positions of capacitors with screw terminals* "Mounting positions of capacitors with screw terminals* 11.4 "Mounting considerations for single-ended capacitors" 11.4 "Mounting considerations for single-ended capacitors" 11.5 "Mounting torques"	Polanty	· · · ·	-
Reverse voltage Voltages polarity classes should be prevented by connecting a diode. Upper category temperature Do not exceed the upper category temperature. Maintenance Make periodic inspections of the capacitors. Before the inspection, make sure that the power supply is turned off and carefully discharge the electricity of the capacitors. Do not apply any mechanical stress to the capacitor terminals. Mounting position of screw-terminal capacitors Mounting of single-ended capacitors The internal structure of single-ended capacitors might be damaged if excessive force is applied to the lead wires. Avoid any compressive, tensile or flexural stress. Do not move the capacitor after soldering to PC board. Do not pick up the PC board by the soldered capacitor. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals: M5: 2 Nm M6: 2.5 Nm Soldering Do not exceed the specified time or temperature 11.5		with the right polarity.	
Reverse voltage Voltages polarity classes should be prevented by connecting a diode. Upper category temperature Do not exceed the upper category temperature. Maintenance Make periodic inspections of the capacitors. Before the inspection, make sure that the power supply is turned off and carefully discharge the electricity of the capacitors. Do not apply any mechanical stress to the capacitor terminals. Mounting position of screw-terminal capacitors Mounting of single-ended capacitors The internal structure of single-ended capacitors with be damaged if excessive force is applied to the lead wires. Avoid any compressive, tensile or flexural stress. Do not move the capacitor after soldering to PC board. Do not pick up the PC board by the soldered capacitor. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals The following maximum tightening torques must not be exceeded when connecting screw terminals: M5: 2 Nm M6: 2.5 Nm Soldering Do not exceed the specified time or temperature 11.5			,
Upper category temperature Do not exceed the upper category temperature. Maintenance Make periodic inspections of the capacitors. Before the inspection, make sure that the power supply is turned off and carefully discharge the electricity of the capacitors. Do not apply any mechanical stress to the capacitor terminals. Mounting position of screw-terminal capacitors Mounting of single-ended capacitors Mounting of single-ended capacitors Mounting of single-ended capacitors Avoid any compressive, tensile or flexural stress. Do not move the capacitor after soldering to PC board. Do not pick up the PC board by the soldered capacitor. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals: Mounting of single-ended capacitors in the flexibility of the lead space specified. Robustness of terminals: MS: 2 Nm M6: 2.5 Nm Soldering Do not exceed the upper category temperature. 7.2 "Maximum permissible operating temperature. 10 "Maintenance" 11.4 "Mounting positions of capacitors with screw terminals 11.1. "Mounting considerations for single-ended capacitors" 11.4 "Mounting considerations for single-ended capacitors" 11.3 "Mounting torques" 11.3 "Mounting torques"	Povorco voltago	Voltages polarity aleeses should be provented by	· ·
Upper category temperature Do not exceed the upper category temperature. Maintenance Make periodic inspections of the capacitors. Before the inspection, make sure that the power supply is turned off and carefully discharge the electricity of the capacitors. Do not apply any mechanical stress to the capacitor terminals. Mounting position of screw-terminal capacitors Mounting of single-ended capacitors Mounting considerations for single-ended capacitors Do not move the capacitor after soldering to PC board. Do not pick up the PC board by the soldered capacitor. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals The following maximum tightening torques must not be exceeded when connecting screw terminals: Mounting considerations for single-ended capacitors 11.3 Mounting torques' Mounting torques' Mounting torques' Mounting torques' Mounting torques'	neverse voltage		
temperature Maintenance Make periodic inspections of the capacitors. Before the inspection, make sure that the power supply is turned off and carefully discharge the electricity of the capacitors. Do not apply any mechanical stress to the capacitor terminals. Mounting position of screw-terminal capacitors Mounting of single-ended capacitors might be damaged if excessive force is applied to the lead wires. Avoid any compressive, tensile or flexural stress. Do not move the capacitor after soldering to PC board. Do not pick up the PC board by the soldered capacitor. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals: Make periodic inspections of the capacitors. Before the inspection, make sure that the power supplied to gradients. 10 "Maintenance" 11.1. "Mounting positions of capacitors with screw terminals" 11.4 "Mounting considerations for single-ended capacitors provided to a capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals The following maximum tightening torques must not be exceeded when connecting screw terminals: M5: 2 Nm M6: 2.5 Nm Soldering Do not exceed the specified time or temperature 11.5	Hanna and and an and	<u> </u>	
Maintenance Make periodic inspections of the capacitors. Before the inspection, make sure that the power supply is turned off and carefully discharge the electricity of the capacitors. Do not apply any mechanical stress to the capacitor terminals. Mounting position of screw-terminal capacitors Mounting of single-ended capacitors Mounting of single-ended capacitors The internal structure of single-ended capacitors might be damaged if excessive force is applied to the lead wires. Avoid any compressive, tensile or flexural stress. Do not move the capacitor after soldering to PC board. Do not pick up the PC board by the soldered capacitor. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals Robustness of terminals Not be exceeded when connecting screw terminals: M5: 2 Nm M6: 2.5 Nm Soldering Do not exceed the specified time or temperature 11.5		Do not exceed the upper category temperature.	· ·=
Make periodic inspections of the capacitors. Before the inspection, make sure that the power supply is turned off and carefully discharge the electricity of the capacitors. Do not apply any mechanical stress to the capacitor terminals. Mounting position of screw-terminal capacitors Mounting of single-ended capacitors Mounting considerations for single-ended capacitors' Do not move the capacitor after soldering to PC board. Do not pick up the PC board by the soldered capacitor. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals: M5: 2 Nm M6: 2.5 Nm Soldering Make periodic inspections of the that the power sure tha	temperature		•
Before the inspection, make sure that the power supply is turned off and carefully discharge the electricity of the capacitors. Do not apply any mechanical stress to the capacitor terminals. Mounting position of screw-terminal capacitors Mounting of single-ended might be damaged if excessive force is applied to capacitors Mounting of the lead wires. Avoid any compressive, tensile or flexural stress. Do not move the capacitor after soldering to PC board. Do not pick up the PC board by the soldered capacitor. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals Robustness of terminals Robustness of terminals Mointing maximum tightening torques must not be exceeded when connecting screw terminals: M5: 2 Nm M6: 2.5 Nm Soldering Do not exceed the specified time or temperature 11.5			
supply is turned off and carefully discharge the electricity of the capacitors. Do not apply any mechanical stress to the capacitor terminals. Mounting position of screwterminal capacitors Mounting of Single-ended capacitors Mounting of Single-ended capacitors The internal structure of single-ended capacitors might be damaged if excessive force is applied to the lead wires. Avoid any compressive, tensile or flexural stress. Do not move the capacitor after soldering to PC board. Do not pick up the PC board by the soldered capacitor. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals The following maximum tightening torques must not be exceeded when connecting screw terminals: M5: 2 Nm M6: 2.5 Nm Soldering Do not exceed the specified time or temperature 11.5	Maintenance		
electricity of the capacitors. Do not apply any mechanical stress to the capacitor terminals. Mounting position of screwterminal capacitors Mounting of single-ended capacitors Mounting of single-ended capacitors Mounting of single-ended capacitors might be damaged if excessive force is applied to the lead wires. Avoid any compressive, tensile or flexural stress. Do not move the capacitor after soldering to PC board. Do not pick up the PC board by the soldered capacitor. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals The internal structure of single-ended capacitors might be damaged if excessive force is applied to the lead wires. Avoid any compressive, tensile or flexural stress. Do not move the capacitor after soldering to PC board. Do not pick up the PC board by the soldered capacitor. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals The following maximum tightening torques must not be exceeded when connecting screw terminals: M5: 2 Nm M6: 2.5 Nm Soldering Do not exceed the specified time or temperature 11.5		· · · · · · · · · · · · · · · · · · ·	"Maintenance"
Do not apply any mechanical stress to the capacitor terminals. Mounting position of screw-terminal capacitors Mounting of single-ended capacitors might be damaged if excessive force is applied to the lead wires. Avoid any compressive, tensile or flexural stress. Do not move the capacitor after soldering to PC board. Do not pick up the PC board by the soldered capacitor. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals The internal structure of single-ended capacitors might be damaged if excessive force is applied to the lead wires. Avoid any compressive, tensile or flexural stress. Do not move the capacitor after soldering to PC board. Do not pick up the PC board by the soldered capacitor. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals The following maximum tightening torques must not be exceeded when connecting screw terminals: M5: 2 Nm M6: 2.5 Nm Soldering Do not exceed the specified time or temperature 11.5			
capacitor terminals. Mounting position of screw-terminal capacitors Mounting of single-ended capacitors Mounting of single-ended capacitors might be damaged if excessive force is applied to the lead wires. Avoid any compressive, tensile or flexural stress. Do not move the capacitor after soldering to PC board. Do not pick up the PC board by the soldered capacitor. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals The internal structure of single-ended capacitors might be damaged if excessive force is applied to the lead wires. Avoid any compressive, tensile or flexural stress. Do not move the capacitor after soldering to PC board. Do not pick up the PC board by the soldered capacitor. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals M5: 2 Nm M6: 2.5 Nm Soldering Do not exceed the specified time or temperature 11.5			
Mounting position of screw-terminal capacitors with upside down. Mounting position of screw-terminal capacitors with upside down. "Mounting positions of capacitors with screw terminals" 11.4 "Mounting capacitors might be damaged if excessive force is applied to the lead wires. Avoid any compressive, tensile or flexural stress. Do not move the capacitor after soldering to PC board. Do not pick up the PC board by the soldered capacitor. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals The following maximum tightening torques must not be exceeded when connecting screw terminals: M5: 2 Nm M6: 2.5 Nm Soldering Do not exceed the specified time or temperature 11.5			
position of screw- terminal capacitors (safety vent) upside down. "Mounting positions of capacitors with screw terminals" Mounting of single-ended capacitors might be damaged if excessive force is applied to the lead wires. Avoid any compressive, tensile or flexural stress. Do not move the capacitor after soldering to PC board. Do not pick up the PC board by the soldered capacitor. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals The following maximum tightening torques must not be exceeded when connecting screw terminals: M5: 2 Nm M6: 2.5 Nm Soldering Do not exceed the specified time or temperature 11.5	Manustina	-	44.4
terminal capacitors Mounting of single-ended capacitors might be damaged if excessive force is applied to the lead wires. Avoid any compressive, tensile or flexural stress. Do not move the capacitor after soldering to PC board. Do not pick up the PC board by the soldered capacitor. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals The following maximum tightening torques must not be exceeded when connecting screw terminals: M5: 2 Nm M6: 2.5 Nm Soldering Do not exceed the specified time or temperature 11.5	-		
Mounting of single-ended capacitors might be damaged if excessive force is applied to the lead wires. Avoid any compressive, tensile or flexural stress. Do not move the capacitor after soldering to PC board. Do not pick up the PC board by the soldered capacitor. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals The following maximum tightening torques must not be exceeded when connecting screw terminals: M5: 2 Nm M6: 2.5 Nm Soldering Do not exceed the specified time or temperature 11.5		(salety verit) upside down.	
Mounting of single-ended capacitors might be damaged if excessive force is applied to the lead wires. Avoid any compressive, tensile or flexural stress. Do not move the capacitor after soldering to PC board. Do not pick up the PC board by the soldered capacitor. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals The following maximum tightening torques must not be exceeded when connecting screw terminals: M5: 2 Nm M6: 2.5 Nm Soldering Do not exceed the specified time or temperature 11.5	terriiriai capacitors		
single-ended capacitors might be damaged if excessive force is applied to the lead wires. Avoid any compressive, tensile or flexural stress. Do not move the capacitor after soldering to PC board. Do not pick up the PC board by the soldered capacitor. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals not be exceeded when connecting screw terminals: M5: 2 Nm M6: 2.5 Nm Soldering Do not exceed the specified time or temperature 11.5	Mounting of	The internal structure of single-ended canacitors	
the lead wires. Avoid any compressive, tensile or flexural stress. Do not move the capacitor after soldering to PC board. Do not pick up the PC board by the soldered capacitor. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals The following maximum tightening torques must not be exceeded when connecting screw terminals: M5: 2 Nm M6: 2.5 Nm Soldering Do not exceed the specified time or temperature 11.5	•		
Avoid any compressive, tensile or flexural stress. Do not move the capacitor after soldering to PC board. Do not pick up the PC board by the soldered capacitor. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals The following maximum tightening torques must not be exceeded when connecting screw terminals: M5: 2 Nm M6: 2.5 Nm Soldering Do not exceed the specified time or temperature 11.5	•		9
Do not move the capacitor after soldering to PC board. Do not pick up the PC board by the soldered capacitor. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals not be exceeded when connecting screw terminals: M5: 2 Nm M6: 2.5 Nm Soldering Do not exceed the specified time or temperature 11.5	σαρασιτοίο		
board. Do not pick up the PC board by the soldered capacitor. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals The following maximum tightening torques must not be exceeded when connecting screw terminals: M5: 2 Nm M6: 2.5 Nm Soldering Do not exceed the specified time or temperature 11.5			omgro oridod odpaditoro
capacitor. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals The following maximum tightening torques must not be exceeded when connecting screw terminals: M5: 2 Nm M6: 2.5 Nm Soldering Do not exceed the specified time or temperature 11.5			
capacitor. Do not insert the capacitor on the PC board with a hole space different to the lead space specified. Robustness of terminals The following maximum tightening torques must not be exceeded when connecting screw terminals: M5: 2 Nm M6: 2.5 Nm Soldering Do not exceed the specified time or temperature 11.5		Do not pick up the PC board by the soldered	
hole space different to the lead space specified. Robustness of terminals The following maximum tightening torques must not be exceeded when connecting screw terminals: M5: 2 Nm M6: 2.5 Nm Soldering Do not exceed the specified time or temperature 11.5			
Robustness of terminals The following maximum tightening torques must not be exceeded when connecting screw terminals: M5: 2 Nm M6: 2.5 Nm Soldering Do not exceed the specified time or temperature 11.5		Do not insert the capacitor on the PC board with a	
terminals not be exceeded when connecting screw terminals: M5: 2 Nm M6: 2.5 Nm Soldering Do not exceed the specified time or temperature 11.5		hole space different to the lead space specified.	
terminals: M5: 2 Nm M6: 2.5 Nm Soldering Do not exceed the specified time or temperature 11.5	Robustness of	The following maximum tightening torques must	11.3
M5: 2 Nm M6: 2.5 Nm Soldering Do not exceed the specified time or temperature 11.5	terminals	not be exceeded when connecting screw	"Mounting torques"
M6: 2.5 Nm Soldering Do not exceed the specified time or temperature 11.5		terminals:	
Soldering Do not exceed the specified time or temperature 11.5		M5: 2 Nm	
limits during soldering. "Soldering"	Soldering	Do not exceed the specified time or temperature	' ' ' '
		limits during soldering.	"Soldering"





High performance - 105 °C

Topic	Safety information	Reference chapter "General technical information"
Soldering, cleaning agents	Do not allow halogenated hydrocarbons to come into contact with aluminum electrolytic capacitors.	11.6 "Cleaning agents"
Passive flammability	Avoid external energy, such as fire or electricity.	8.1 "Passive flammability"
Active flammability	Avoid overload of the capacitors.	8.2 "Active flammability"
		Reference chapter "Capacitors with screw terminals"
Breakdown strength of insulating sleeves	Do not damage the insulating sleeve, especially when ring clips are used for mounting.	"Screw terminals – accessories"



High performance − 105 °C



Symbols and terms

Symbol	English	German
С	Capacitance	Kapazität
C_R	Rated capacitance	Nennkapazität
Cs	Series capacitance	Serienkapazität
$C_{\text{S,T}}$	Series capacitance at temperature T	Serienkapazität bei Temperatur T
C_{f}	Capacitance at frequency f	Kapazität bei Frequenz f
d	Case diameter, nominal dimension	Gehäusedurchmesser, Nennmaß
d_{max}	Maximum case diameter	Maximaler Gehäusedurchmesser
ESL	Self-inductance	Eigeninduktivität
ESR	Equivalent series resistance	Ersatzserienwiderstand
ESR _f	Equivalent series resistance at frequency f	Ersatzserienwiderstand bei Frequenz f
ESR _T	Equivalent series resistance at temperature T	Ersatzserienwiderstand bei Temperatur T
f	Frequency	Frequenz
1	Current	Strom
I _{AC}	Alternating current (ripple current)	Wechselstrom
$\mathbf{I}_{AC,rms}$	Root-mean-square value of alternating current	Wechselstrom, Effektivwert
$I_{AC,f}$	Ripple current at frequency f	Wechselstrom bei Frequenz f
$I_{AC,max}$	Maximum permissible ripple current	Maximal zulässiger Wechselstrom
$I_{AC,R}$	Rated ripple current	Nennwechselstrom
I _{AC,R} (B)	Rated ripple current for base cooling	Nennwechselstromstrom für Bodenkühlung
I _{leak}	Leakage current	Reststrom
$I_{leak,op}$	Operating leakage current	Betriebsreststrom
I	Case length, nominal dimension	Gehäuselänge, Nennmaß
I _{max}	Maximum case length (without terminals and mounting stud)	Maximale Gehäuselänge (ohne Anschlüsse und Gewindebolzen)
R	Resistance	Widerstand
R_{ins}	Insulation resistance	Isolationswiderstand
R_{symm}	Balancing resistance	Symmetrierwiderstand
T	Temperature	Temperatur
ΔT	Temperature difference	Temperaturdifferenz
T_A	Ambient temperature	Umgebungstemperatur
T_C	Case temperature	Gehäusetemperatur
T_B	Capacitor base temperature	Temperatur des Becherbodens
t	Time	Zeit
Δt	Period	Zeitraum
t_b	Service life (operating hours)	Brauchbarkeitsdauer (Betriebszeit)





High performance - 105 °C

Symbol	English	German
V	Voltage	Spannung
V_{F}	Forming voltage	Formierspannung
V_{op}	Operating voltage	Betriebsspannung
V_R	Rated voltage, DC voltage	Nennspannung, Gleichspannung
V_s	Surge voltage	Spitzenspannung
X_{C}	Capacitive reactance	Kapazitiver Blindwiderstand
X_L	Inductive reactance	Induktiver Blindwiderstand
Z	Impedance	Scheinwiderstand
Z_T	Impedance at temperature T	Scheinwiderstand bei Temperatur T
$tan \ \delta$	Dissipation factor	Verlustfaktor
λ	Failure rate	Ausfallrate
ϵ_{0}	Absolute permittivity	Elektrische Feldkonstante
ϵ_{r}	Relative permittivity	Dielektrizitätszahl
ω	Angular velocity; $2 \cdot \pi \cdot f$	Kreisfrequenz; $2 \cdot \pi \cdot f$

Note

All dimensions are given in mm.



Important notes

The following applies to all products named in this publication:

- 1. Some parts of this publication contain statements about the suitability of our products for certain areas of application. These statements are based on our knowledge of typical requirements that are often placed on our products in the areas of application concerned. We nevertheless expressly point out that such statements cannot be regarded as binding statements about the suitability of our products for a particular customer application. As a rule, EPCOS is either unfamiliar with individual customer applications or less familiar with them than the customers themselves. For these reasons, it is always ultimately incumbent on the customer to check and decide whether an EPCOS product with the properties described in the product specification is suitable for use in a particular customer application.
- 2. We also point out that in individual cases, a malfunction of electronic components or failure before the end of their usual service life cannot be completely ruled out in the current state of the art, even if they are operated as specified. In customer applications requiring a very high level of operational safety and especially in customer applications in which the malfunction or failure of an electronic component could endanger human life or health (e.g. in accident prevention or lifesaving systems), it must therefore be ensured by means of suitable design of the customer application or other action taken by the customer (e.g. installation of protective circuitry or redundancy) that no injury or damage is sustained by third parties in the event of malfunction or failure of an electronic component.
- 3. The warnings, cautions and product-specific notes must be observed.
- 4. In order to satisfy certain technical requirements, some of the products described in this publication may contain substances subject to restrictions in certain jurisdictions (e.g. because they are classed as hazardous). Useful information on this will be found in our Material Data Sheets on the Internet (www.epcos.com/material). Should you have any more detailed questions, please contact our sales offices.
- 5. We constantly strive to improve our products. Consequently, the products described in this publication may change from time to time. The same is true of the corresponding product specifications. Please check therefore to what extent product descriptions and specifications contained in this publication are still applicable before or when you place an order. We also reserve the right to discontinue production and delivery of products. Consequently, we cannot guarantee that all products named in this publication will always be available. The aforementioned does not apply in the case of individual agreements deviating from the foregoing for customer-specific products.
- Unless otherwise agreed in individual contracts, all orders are subject to the current version of the "General Terms of Delivery for Products and Services in the Electrical Industry" published by the German Electrical and Electronics Industry Association (ZVEI).
- 7. The trade names EPCOS, BAOKE, Alu-X, CeraDiode, CSMP, CSSP, CTVS, DeltaCap, DigiSiMic, DSSP, FormFit, MiniBlue, MiniCell, MKK, MKD, MLSC, MotorCap, PCC, PhaseCap, PhaseCube, PhaseMod, PhiCap, SIFERRIT, SIFI, SIKOREL, SilverCap, SIMDAD, SiMic, SIMID, SineFormer, SIOV, SIP5D, SIP5K, ThermoFuse, WindCap are trademarks registered or pending in Europe and in other countries. Further information will be found on the Internet at www.epcos.com/trademarks.