

Bulgin's extensive range of fuseholders are designed to give the degree of protection demanded in today's sophisticated electronic equipment. Carrying world-wide safety approvals from UL, VDE, CSA and IMQ, all types are manufactured from high grade flame retardant nylon and polyester materials.

Designed primarily for 5 x 20mm and 6.3 x 32mm size fuses with protection against shock to categories PC1, PC2 and PC3. There's a choice of styles for in-line, PCB mounting and panel mounting (screw or snap fit) with terminal options for solder, 2.8mm, 4.8mm or 6.3mm tabs or PC spills. Dust and waterproof designs provide a front of panel seal to IP68 in both 5 x 20mm and 6.3 x 32mm size fuses.

Fuse carrier styles include captive drawer, screw cap - with screw driver release, bayonet cap - with screw driver release and screw cap - with finger release.

Panel/PC Mounting Captive Carriers Touchproof, PC3 Panel Mounting Touchproof, Sealed to IP68, PC2 Panel Mounting Touchproof, Sealed to IP66, PC1 PC Mounting PC1, PC2 and PC3 Base Mounting, PC1

In-Line PC1 and In-Line Sealed to IP66, PC1





Fuseholders

Protection Category



Category PC1:

No integral protection against electric shock. If required, Designers/ Manufacturers must provide additional protection against electric shock on equipment.

Category PC2:

With integral protection against electric shock. Fuseholders shall have live parts inaccessible to IEC 60529 Standard Test Finger, when fully assembled, without fuse carrier or fuse in place and when fuse carrier, with fuse is being inserted or withdrawn.

Category PC3:

With integral protection against electric shock. Fuseholders shall have live parts inaccessible to IEC 60529 1mm dia. rigid test wire when fully assembled, without fuse carrier or fuse in place and when fuse carrier, with fuse, is being inserted or withdrawn.

Panel/PC Mounting Captive Carriers Touchproof, PC3




Snap Fit to Panel



Fuse Size 5 x 20mm Panel Sizes 1.0, 1.5, 2.0 and 3.0mm

O Protection Category PC3

- Captive Drawer 10A, 250V (16A, 250V UL)
- 2.8, 4.8 or 6.3 tabs



Snap Fit to Panel



FX0430/PC


Compliant

FX0430/63

- O Protection Category PC3
- Fuse Size 5 x 20mm
- Panel Sizes 1.0, 1.5, 2.0 and 3.0mm
- Captive Drawer
- 10A, 250V (16A, 250V UL)

Compliant

O PC spills



Specifications	FX0430/Termination	FX0430/PC
Fuse Size:	5 x 20mm	5 x 20mm
Fuse Carrier:	Captive Drawer	Captive Drawer
Terminations:	/28 (2.8mm solder), /48 (4.8mm tab), /63 (6.3mm tab)	/PC (PC spills)
Max. Rating:	10A, 250V (16A, 250V a.c. UL)	10A, 250V (16A, 250V a.c. UL)
Max. Power Dissipation:	2.5W (@ 23°C)	2.5W (@ 23°C)
Insulation Resistance:	>10MΩ @ 500V d.c.	>10MΩ @ 500V d.c.
A.C. Breakdown:	>2kV	>2kV
Contact Resistance:	<10mΩ	<10mΩ
Operating Temp:	-20°C to +85°C (ambient air temp + fuse temp rise)	-20°C to +85°C (ambient air temp + fuse temp rise)
Mouldings: Body/Drawer: Cap: Nut:	Nylon UL94V-0 rated	Nylon UL94V-0 rated
Contacts:	Contact tags: Brass, Tin Plated Fuse Clips: Phospher Bronze, Nickel Plated	Contact tags: Brass, Tin Plated Fuse Clips: Phospher Bronze, Nickel Plated
Approvals:		
Accessories:		
Note:		

Panel Mounting and Snap Fit Touchproof, PC2








FX0357

FX0359

- O Protection Category PC2
- 0 Fuse Size 5 x 20mm
- Bayonet Cap/Screwdriver Release
- 10A, 250V (16A, 250V UL)




Snap Fit to Panel



FX0367

FX0369

- \bigcirc Protection Category PC2
- Fuse Size 5 x 20mm
- Panel Sizes 1.0 & 1.5 and 2.0 & 3.0mm
- Bayonet Cap/Screwdriver Release
- 10A, 250V (16A, 250V UL)



Specifications	FX0357, FX0359

Fuse Size: 5 x 20mm

Panel Size: /1 (1.0-1.5mm panel, black sleeve)

/2 (2.0-3.0mm panel, grey sleeve)

FX0367/Panel, FX0369/Panel

Fuse Carrier: Bayonet cap/Screwdriver release Bayonet cap/Screwdriver release

Terminations: Solder tags Solder tags

10A, 250V (16A, 250V a.c. UL) 10A, 250V (16A, 250V a.c. UL) Max. Rating:

2.5W (@ 23°C) 2.5W (@ 23°C) Max. Power Dissipation:

Insulation Resistance: $>10^2 M\Omega$ @ 500V d.c. $>10^{2}M\Omega$ @ 500V d.c.

A.C. Breakdown: 7kV @ 50Hz 7kV @ 50Hz Contact Resistance: <10mΩ <10mΩ

-20°C to +85°C -20°C to +85°C Operating Temp:

(ambient air temp + fuse temp rise) (ambient air temp + fuse temp rise)

Mouldings:

Body: Polyester UL94V-0 rated Nylon UL94V-0 rated Cap: Glass Filled Nylon UL94V-0 rated

Contacts: Brass, Silver Plated

*VDE APPROVALS PENDING **FL** (1) Approvals:

Accessories: P.No. 11327 (See page 206) P.No. 11327 (See page 205)

RoHS Compliant

Polyester UL94V-0 rated Nylon UL94V-0 rated

Brass, Silver Plated

Compliant

Panel Mounting and Snap Fit Touchproof, PC2








FX0454,

FX0455

- Protection Category PC2
- Fuse Size 5 x 20mm
- Screw Cap/Screwdriver Release
- \bigcirc Keyway Panel Cutout (FX0454)
- \Diamond D Panel Cutout (FX0455)
- 10A, 250V (16A, 250V UL)




Panel Mount



FX0454/S

FX0455/S


- Protection Category PC2
- Fuse Size 5 x 20mm
- Screw Cap/Screwdriver Release
- ŏ High Profile Bezel
- Keyway Panel Cutout (FX0454/S)
- D Panel Cutout (FX0455/S)
- 10A, 250V (16A, 250V UL)



Snap Fit to Panel



- FX0458
- Protection Category PC2
- Fuse Size 5 x 20mm
- Panel Sizes 1.0 & 1.5 and
- \bigcirc 2.0 & 3.0mm
- Screw Cap/Screwdriver Release
- 10A, 250V (16A, 250V UL)



FX0458/I FX0458/2

Panel Thickness 1.0 & 1.5 2.0 & 3.0

Specifications	FX0454, FX0455	FX0454/S, FX0455/S	FX0458
Fuse Size:	5 x 20mm	5 x 20mm	5 x 20mm
Panel Size:			/1 (1.0-1.5mm panel, black sleeve) /2 (2.0-3.0mm panel, grey sleeve)
Fuse Carrier:	Screw cap/Screwdriver release	Screw cap/Screwdriver release	Screw cap/Screwdriver release
Terminations:	Solder tags	Solder tags	Solder tags
Max. Rating:	10A, 250V (16A, 250V a.c. UL)	10A, 250V (16A, 250V a.c. UL)	10A, 250V (16A, 250V a.c. UL)
Max. Power Dissipation:	2.5W (@ 23°C)	2.5W (@ 23°C)	2.5W (@ 23°C)
Insulation Resistance:	>10 2 M Ω @ 500V d.c.	$>10^2 M\Omega$ @ 500V d.c.	$>10^2 M\Omega$ @ 500V d.c.
A.C. Breakdown:	7kV @ 50Hz	7kV @ 50Hz	7kV @ 50Hz
Contact Resistance:	<10mΩ	<10mΩ	<10mΩ
Operating Temp: Mouldings:	-20°C to +85°C (ambient air temp + fuse temp rise)	-20°C to +85°C (ambient air temp + fuse temp rise)	-20°C to +85°C (ambient air temp + fuse temp rise)
Body: Cap: Nut:	Polyester UL94V-0 rated Nylon UL94V-0 rated Glass Filled Nylon UL94V-0 rated	Polyester UL94V-0 rated Nylon UL94V-0 rated Glass Filled Nylon UL94V-0 rated	Polyester UL94V-0 rated Nylon UL94V-0 rated
Contacts:	Brass, Silver Plated	Brass, Silver Plated	Brass, Silver Plated
Approvals:	A B A	91.0	A B
Accessories:	P.Nos. 11327, 12297 & 12298 (See page 206)	P.Nos. 11327, 12297 & 12298 (See page 206)	P.Nos. 11327 (See page 205)
RoHS	Compliant	Compliant	Compliant

Panel Mounting Touchproof, PC2



Panel Mount




FX0415,

FX0416

Protection Category PC2

Fuse Sizes:6.3 x 32mm (FX0415)6.3 x 25mm (FX0416)

- Screw Cap/Hand Release
- 13A, 250V (16A, 250V UL)



Panel Mount

Specifications


Contact Resistance:



Protection Category PC2

Fuse Sizes: 6.3 x 32mm (FX0415/S) 6.3 x 25mm (FX0416/S)

- Screw Cap/Screwdriver
- 13A, 250V (16A, 250V UL)



FX0415/S, FX0416/S

 $<5m\Omega$

FX0415/S,	FXU416/

 $<5m\Omega$

Fuse Size: FX0415 - 6.3 x 32mm FX0416/S - 6.3 x 32mm FX0416/S - 6.3 x 25mm FX0416/S - 6.3 x 25mm

Fuse Carrier: Screw cap/Hand release Screw cap/Hand release

 Terminations:
 4.8 series tabs
 4.8 series tabs

 Max. Rating:
 13A, 250V (16A, 250V UL)
 13A, 250V (16A, 250V UL)

 Max. Power Dissipation:
 4W (@ 23°C)
 4W (@ 23°C)

FX0415, FX0416

Insulation Resistance: $>10^5 M\Omega$ @ 500V d.c. $>10^5 M\Omega$ @ 500V d.c.

A.C. Breakdown: 4kV @ 50Hz 4kV @ 50Hz

Operating Temp: -20°C to +85°C -20°C to +85°C (ambient air temp + fuse temp rise) -20°C to +85°C (ambient air temp + fuse temp rise)

Mouldings:
Body: Glass Filled Nylon UL94V-0 rated Glass Filled Nylon UL94V-0 rated
Cap: Nylon UL94V-0 rated Nylon UL94V-0 rated
Nut: Polyester UL94V-0 rated Polyester UL94V-0 rated
Contacts: Brass, Silver Plated Brass, Silver Plated

Approvals:

Accessories: P.No. 12932 (See page 205) P.No. 12932 (See page 205)

HS Compliant Compliant

Panel Mounting, PC2




Panel Mount



FX0354

- O Protection Category PC2
- \bigcirc Low Profile Bezel
- Fuse Size 5 x 20mm
- Screw Cap/Screwdriver Release
- Keyway Panel Cutout
- 6.3A, 250V



Panel Mount


RoHS



FX0354/S

Compliant

- Protection Category PC2
- 0 High Profile Bezel
- Fuse Size 5 x 20mm
- Screw Cap/Screwdriver Release
- Keyway Panel Cutout
- 6.3A, 250V



	171000 1/0	
Specifications	FX0354	FX0354/S
Fuse Size:	5 x 20mm	5 x 20mm
Fuse Carrier:	Screw cap/Screwdriver release	Screw cap/Screwdriver release
Terminations:	Solder tags	Solder tags
Max. Rating:	6.3A, 250V	6.3A, 250V
Max. Power Dissipation:	2.5W (@ 23°C)	2.5W (@ 23°C)
Insulation Resistance:	$>$ 10 2 M Ω @ 500V d.c.	$>10^2 M\Omega$ @ 500V d.c.
A.C. Breakdown:	5kV @ 50Hz	5kV @ 50Hz
Contact Resistance:	<10mΩ	<10mΩ
Operating Temp:	-20°C to +85°C (ambient air temp + fuse temp rise)	-20°C to +85°C (ambient air temp + fuse temp rise)
Mouldings: Body: Cap: Nut:	Polyester UL94V-0 rated Nylon UL94V-0 rated Glass Filled Nylon UL94V-0 rated	Polyester UL94V-0 rated Nylon UL94V-0 rated Glass Filled Nylon UL94V-0 rated
Contacts:	Brass, Silver Plated	Brass, Silver Plated
Approvals:		
Accessories:	P.No. 11327 and 12298 (See page 205)	P.No. 11327 and 12298 (See page 205)

Compliant

Fuseholders 6.3 x 32mm (11/4" x 1/4"), PC2





Key Features

- O 6.3 x 32mm fuses
- Screwdriver slot knob
- PC2 protection category
- 4.8, 6.3 and solder terminals
- Low profile bezel
- Snap in or threaded bushing mounting options

Approvals and specifications

(Z)

10A 250V (max fuse rating*) T–55 to T+70 (ambient) Maximum dissipation wattage: 4W

16 16A UL 250V UL file E92075 CSA file LR44770

These products comply with safety category PC2. *Users should be aware of the de-rating factors published by specialist manufacturers of fuses.

Fuseholders with in-line termination have combination (4.8/6.3) terminals. It has not been possible to show both views here. Units with right angle terminals have user specified end terminals and combination mid-body terminals.





Fuseholders Panel Mounting, PC1




Panel Mount



FX0296/S

FX0296


- O Protection Category PC1
- Fuse Size 5
 Screw Cap/
 6.3A, 250V Fuse Size 5 x 20mm
- Screw Cap/Hand Release



Panel Mount



- FX0296/1
- O Protection Category PC1
- Fuse Size 5 x 20mm
 Screw Cap/Hand Rel
 6.3A, 250V
- Screw Cap/Hand Release



Specifications	FX0296, FX0296/S	FX0296/1
Fuse Size:	5 x 20mm	5 x 20mm
Fuse Carrier:	FX0296 Screw cap/Hand release FX0296/S Screw cap/Screwdriver release	Screw cap/Hand release
Terminations:	Solder tags	Solder tags
Max. Rating:	6.3A, 250V	6.3A, 250V
Max. Power Dissipation:	2.5W (@ 23°C)	2.5W (@ 23°C)
Insulation Resistance:	>10 ⁵ MΩ @ 500V d.c.	$>10^5 M\Omega$ @ 500V d.c.
A.C. Breakdown:	2.5kV @ 50Hz	2.5kV @ 50Hz
Contact Resistance:	<5mΩ	<5mΩ
Operating Temp:	-20°C to +85°C (ambient air temp + fuse temp rise)	-20°C to +85°C (ambient air temp + fuse temp rise)
Mouldings: Body: Cap: Nut:	Glass Filled Nylon UL94V-0 rated Nylon UL94V-0 rated Glass Filled Nylon UL94V-0 rated	Glass Filled Nylon UL94V-0 rated Nylon UL94V-0 rated Glass Filled Nylon UL94V-0 rated
Contacts:	Brass, Silver or Tin Plated	Brass, Silver or Tin Plated
Accessories	P.No. 9820 (See page 205)	P.No. 9820 (See page 205)
RoHS	Compliant	Compliant

Panel Mounting Touchproof, Sealed to IP68, PC2




Panel Mount



FX0419

- Panel sealed to IP68
- Touchproof Category PC2
- Fuse Size 6.3 x 32mm
- Screw cap/Screwdriver/Hand Release
- 16A. 250V ac




Panel Mount



FX0462


- Panel sealed to IP68
- Touchproof Category PC2
- Fuse Size 5 x 20mm
- Screw cap/Screwdriver/Hand Release
- 10A. 250V ac



Panel Mount



- Panel sealed to IP68 Touchproof Category PC2
- Fuse Size 5 x 20mm
- High Profile Bezel
- Screw cap/Screwdriver/Hand Release
- 10A. 250V ac



Specifications	FX0419	FX0462	FX0463
Fuse Size:	6.3 x 32mm	5.0 x 20mm	5.0 x 20mm
Fuse Carrier:	Screw cap/Screwdriver/Hand release	Screw cap/Screwdriver/Hand release	Screw cap/Screwdriver/Hand release
Terminations:	6.3 series tabs	Solder tags	Solder tags
Max. Rating:	16A, 250V ac	10A, 250V ac	10A, 250V ac
Max. Power Dissipation:	2.5W (@ 23°C)	2.5W (@ 23°C)	2.5W (@ 23°C)
Insulation Resistance:	$>10^6 M\Omega$ @ 500V d.c.	$>10^2 M\Omega$ @ 500V d.c.	$>10^2 M\Omega$ @ 500V d.c.
A.C. Breakdown:	>2kV @ 50Hz	>7kV @ 50Hz	>7kV @ 50Hz
Contact Resistance:	<10mΩ	<10mΩ	<10mΩ
Operating Temp:	-20°C to +85°C (ambient air temp + fuse temp rise)	-20°C to +85°C (ambient air temp + fuse temp rise)	-20°C to +85°C (ambient air temp + fuse temp rise)
Mouldings: Body: Cap: Nut:	Polyester UL94V-0 rated Nylon UL94V-0 rated Glass Filled Nylon UL94V-0 rated	Polyester UL94V-0 rated Nylon UL94V-0 rated Glass Filled Nylon UL94V-0 rated	Polyester UL94V-0 rated Nylon UL94V-0 rated Glass Filled Nylon UL94V-0 rated
Contacts:	Brass, Silver Plated	Brass, Silver Plated	Brass, Silver Plated
Tightening Torque: Cap: Panel Nut:	0.5 - 0.6Nm (4.43-5.3lbf.in.) 0.5Nm (4.4lbf.in.)	0.4 - 0.6Nm (3.54-5.3lbf.in.) 0.5Nm (4.4lbf.in.)	0.4 - 0.6Nm (3.54-5.3lbf.in.) 0.5Nm (4.4lbf.in.)
Sealing:	IP68 to EN60529:1992+A2:2013 (10m for 2weeks)	IP68 to EN60529:1992+A2:2013 (10m for 2weeks)	IP68 to EN60529:1992+A2:2013 (10m for 2weeks)
Accessories:		P.nos. 11327 (see page 205)	P.nos. 11327 (see page 205)
Approvals:	*VDE APPROVALS PENDING	A B A	71 6 4
RoHS	Compliant	Compliant	Compliant

Panel Mounting Touchproof, Sealed to IP66, PC1




High Profile Panel Mount



FX0345


- O Sealed to IP66
- Protection Category PC1
- Fuse Size 5 x 20mm
- Screw Cap/Screwdriver Release
- O 6.3A, 250V



High Profile Panel Mount



- O Sealed to IP66
- **Protection Category PC1**
- O Fuse Size 5 x 20mm
- Screw Cap/Hand Release
- Large Cap for Easy Grip6.3A, 250V



·XC	١Q	65	
$\mathcal{N}\mathcal{C}$	$^{\prime}$	00	

Specifications	FX0345, FX0345/A	FX0365, FX0365/A
Fuse Size:	5 x 20mm	5 x 20mm
Fuse Carrier:	Screw cap/Screwdriver release	Screw cap/Screwdriver release
Terminations:	Solder tags	Solder tags
Max. Rating:	6.3A, 250V	6.3A, 250V
Max. Power Dissipation:	4W (@ 23°C)	4W (@ 23°C)
Insulation Resistance:	$>10^3 M\Omega$ @ 500V d.c.	>10³MΩ @ 500V d.c.
A.C. Breakdown:	>3.5kV @ 50Hz	>3.5kV @ 50Hz
Contact Resistance:	<10mΩ	<10mΩ
Operating Temp:	-20°C to +85°C (ambient air temp + fuse temp rise)	-20°C to +85°C (ambient air temp + fuse temp rise)
Mouldings: Body & Cap: Spacer: Insulating Sleeve:	Glass Filled Nylon UL94V-0 rated Glass Filled Nylon UL94HB rated Nylon UL94V-0 rated	Glass Filled Nylon UL94V-0 rated Glass Filled Nylon UL94HB rated Nylon UL94V-0 rated
Contacts:	Brass, Silver Plated	Brass, Silver Plated
Sealing:	Protection Classification IP66 to EN60529:1992+A2:2013 Retains sealing integrity with cap removed since they are both panel and barrier sealed	
Variants:	/A Silicone 'O' ring, Op. Temp. –55°C to +85°C Compliant	/A Silicone 'O' ring, Op. Temp. –55°C to +85°C Compliant


PC Mounting PC1, PC2 and PC3



PC Horizontal Mount



- FX0461
- O Protection Category PC3
- O Fuse Size 5 x 20mm
- Screw Cap/Screwdriver Release
- Captive Fuse Carrier
- PC Spills
- 0 10A, 250V
- (16A, 250V UL)




PC Horizontal and Vertical Mount



FX0457

FX0456

- **Protection Category PC2**
- Fuse Sizes 5 x 20mm
- Bayonet Cap/Screwdriver Release
- O 10A, 250V




PC Horizontal Mount



FX0330

- O Protection Category PC1
- O Fuse Size 5 x 20mm
- ŏ O O
- Two or Three PC Spills Screw Cap/Hand Release
- 6.3A, 250V



Specifications	FX0461	FX0456 FX0457	FX0330 FX0342
Fuse Size:	5 x 20mm	5 x 20mm	5 x 20mm
Fuse Carrier:	Screw cap/Screwdriver release	Bayonet cap/Screwdriver release	Screw cap/Hand release
Terminations:	PC Spills	PC Spills	FX0330 - 3 PC Spills
Max. Rating:	10A, 250V (16A, 250V a.c. UL)	10A, 250V	FX0342 - 2 PC Spills 6.3A, 250V
Max. Power Dissipation:	1.6W (@ 23°C)	2.5W (@ 23°C)	2.5W (@ 23°C)
nsulation Resistance:	>10MΩ @ 500V d.c.	$>10^2 M\Omega$ @ 500V d.c.	$>10^4 M\Omega$ @ 500V d.c.
A.C. Breakdown:	>2kV	4kV @ 50Hz	6kV @ 50Hz
Contact Resistance:	<10mΩ	<10mΩ	<5mΩ
Operating Temp:	-20°C to +85°C (ambient air temp + fuse temp rise)	-20°C to +85°C (ambient air temp + fuse temp rise)	-20°C to +85°C (ambient air temp + fuse temp rise)
Mouldings: Body: Cap: End Bung:	Polyester UL94V-0 rated Nylon UL94V-0 rated	Polyester UL94V-0 rated Nylon UL94V-0 rated Polyester UL94V-0 rated	Glass Filled Nylon UL94V-0 rated Nylon UL94V-0 rated
Contacts:	Brass, Silver Plated	Brass, Silver Plated	Brass, Tin Plated
Approvals:	71 (1) (1)	71 (
RoHS	Compliant	Compliant	Compliant


PC and Base Mounting, PC1







- O Protection Category PC1 O Fuse Size 5 x 20mm
- PC Spills6.3A, 250V




Base Mount



FX0267


- Protection Category PC1Fuse Size 5 x 20mm
- Solder Tags
- 6.3A, 250V



Base Mount



- O Protection Category PC1
- Fuse Size 5 x 20mm
- Solder Tags
- 6.3A, 250V



Specifications	FX0321	FX0267	FX0360
Fuse Size:	5 x 20mm	5 x 20mm	5 x 20mm
Terminations:	PC Spills	Solder tags	Solder tags
Max. Rating:	6.3A, 250V	6.3A, 250V	6.3A, 250V
Insulation Resistance:	$>10^5 \mathrm{M}\Omega$ @ 500V d.c.	$>10^5$ M Ω @ 500V d.c.	$>10^4$ M Ω @ 500V d.c.
A.C. Breakdown:	7kV @ 50Hz (Clip to clip)	1.5kV @ 50Hz	2kV @ 50Hz
Contact Resistance:	<10mΩ	<10mΩ	<10mΩ
Operating Temp: (ambient air temp + fuse temp rise)	–20°C to +85°C	-20°C to +85°C	–20°C to +85°C
Base Material:	Glass Filled Nylon UL94V-0 rated	Glass Filled Nylon UL94V-0 rated	Glass Filled Nylon UL94HB rated
Contacts:	Phospher Bronze, Tin Plated	Phospher Bronze, Tin Plated	Phospher Bronze, Tin Plated
Accessories:	P.No. 12760 (See page 205)	P.No. 12760 (See page 205)	
RoHS	Compliant	Compliant	Compliant

Base Mounting, PC1






O Protection Category PC1

Fuse Sizes: 6.3 x 32mm (FX0326) 6.3 x 25mm (FX0331)

O Solder Tags


○ 13A, 250V



Base Mount



- Protection Category PC1 Fuse Size 6.3 x 32mm
- Solder Tags
- O 5A, 250V



Specifications	FX0326, FX0331	FX0327
Fuse Size:	FX0326 - 6.3 x 32mm FX0331 - 6.3 x 25mm	6.3 x 32mm
Terminations:	6.3 series tabs	Solder tags
Max. Rating:	13A, 250V	5A, 250V
Insulation Resistance:	$>10^4$ M Ω @ 500V d.c.	$>10^5\mathrm{M}\Omega$ @ 500V d.c.
A.C. Breakdown:	5kV @ 50Hz	5kV @ 50Hz
Contact Resistance:	<5mΩ	<10mΩ
Operating Temp: (ambient air temp + fuse temp rise)	–20°C to +85°C	-20°C to +85°C
Base Material:	Glass Filled Polyester UL94V-0 rated	Glass Filled Polyester UL94V-0 rated
Contacts:	Clips: Phospher Bronze, Tin Plated Tabs: Brass, Tin Plated	Phospher Bronze, Tin Plated
RoHS	Compliant	Compliant

In-Line PC1 and In-Line Sealed to IP66, PC1








FX0180, FX0280,

FX0380

- Protection Category PC1
- Fuse Sizes 5 x 20mm,
 - 6.3 x 25mm and 6.3 x 32mm Screw Terminal (Solder to order)
- 0 10A, 50V (250V Inaccessible)
- UL Approved (Black Only)
- Clear or black



In-line



FX0185,

FX0285.

FX0385

- \Diamond Sealed to IP66
- **Protection Category PC1**
- Fuse Sizes 5 x 20mm, 6.3 x 25mm and 6.3 x 32mm
- Screw Terminal (Solder to order)
- 10A, 50V (250V Inaccessible)
- \bigcirc UL Approved (Black Only)
- Clear or black

1.0	Α	-
Stage 1 Stage 2 Stage 3	List No FX0185 FX0285 FX0385	DIM A 91.0 85.2 78.7 +/-0.9

Specifications	FX0180/colour, I	FX0280.colour,	FX0380/Colour

Fuse Size:	5 x 20mm	FX0380
	6.3 x 25mm	FX0280
	6.3 x 32mm	FX0180

Cable Acceptance: 1mm² conductor (max.)

Terminations: Screw terminal (solder to order)

10A, 50V (250V where Max. Rating:

inaccessible inside equipment)

 $>10^{5}$ M Ω @ 500V d.c.

Insulation Resistance: High Voltage Proof Test: Contact Resistance:

2kV (50Hz for 1 minute)

Operating Temp: (ambient air temp + fuse temp rise)

-20°C to +90°C

Sealing:

Screw Tightening Torque 0.226Nm (2lb/in)

Mouldings: Body - Clear:

Body - Black: Grommet: O Ring: Contacts:

Polybutene UL94HB rated Nylon 6 UL94V-0 rated

Terminals: Brass, Nickel Plated Grub Screw: Stainless Steel

Approvals: (Black version only)

Clear - no suffix, /BK - Black RoHS Compliant

6.3 x 25mm 6.3 x 32mm

> Stepped grommet: Stage 1: 1.00mm to 1.40mm Stage 2: 1.50mm to 1.90mm

Stage 3: 2.0mm to 2.64mm

Protection Classification IP66

Nylon 6 UL94V-0 rated

Stainless Steel

Clear - no suffix, /BK - Black

Compliant

Accessories




Insualtion Boots



PNo. 11327 PNo. 9820 PNo. 12932

- O Provide Insulation against Shock on Rear of Fuseholder
- PVC \bigcirc
- UL94V-0 rated flame retardant material




Insualtion Cover



PNo. 12760

- Provide Insulation from Live Parts on Fuseholder
- \bigcirc Clear
- Polycarbonate




Adaptor



PNo. 12297

- Adaptor to Convert Fixing Holes
- Maintains Anti-Rotation
- Glass Filled Nylon



Accessories	For Use With:
P.No. 9820 (Boot)	FX0296, FX0296/1, FX0296/S
P.No. 11327 (Boot)	FX0354, FX0354/S, FX0357, FX0359, FX0454, FX0454/S, FX0455, FX0455/S, FX0460, FX0458, FX0367, FX0369, FX0462, FX0463
P.No. 12932 (Boot)	FX0415, FX0415/S, FX0416, FX0416/S
P.No. 12760 (Cover)	FX0267, FX0321
Max. Working Voltage:	250V a.c.

P.Nos. 9820, 11327, 12932: PVC - UL94V-0 P.No. 12760: Polycarbonate Material:

2kV a.c.

Adapts 'D' fixing to anti-rotation Key Fixing FX0455, FX0455/S $\,$ P.No. 12297

(Adaptor Washer) Glass Filled Nylon Material:

RoHS Compliant

Flash Tested to: