

## Chip POSISTOR®

## muRata

## PRG18 / PRG21 series

(0603 size / 0805 size ) for Over-Current Protection

PRG

Part Number	Resistance (at +25deg.C)	Maximum Voltage	Non-Operating Current (at +60deg.C)	Operating Current (at -10deg.C)
PRG21BB150MB1RK	15 ohm +/-20%	20 VDC	40 mA	140 mA
PRG21BB220MB1RK	22 ohm +/-20%		30 mA	110 mA
PRG18BB330MB1RB	33 ohm +/-20%	24 VDC	25 mA	85 mA
PRG18BB470MB1RB	47 ohm +/-20%		20 mA	75 mA
PRG18BB101MB1RB	100 ohm +/-20%		15 mA	55 mA
PRG18BB221MB1RB	220 ohm +/-20%		10 mA	35 mA
PRG18BB471MB1RB	470 ohm +/-20%		7 mA	25 mA

7	New!		<u> </u>		
4	Part Number	Resistance (at +25deg.C)	Maximum Voltage	Non-Operating Current (at +60deg.C)	Operating Current (at -10deg.C)
	PRG21BC0R2MM1RA	0.20 ohm +/-20%	6 VDC	500 mA	2000 mA